EVAL-FR10DHIR

DC-10 MBd RedLink Evaluation Board User Guide



OVERVIEW

The EVAL-FR10DHIR mini evaluation board enables evaluation and rapid prototyping of the Firecomms RedLink® DC-10 MBd inverting receiver for plastic optic fiber (POF) and large core glass fiber (200, 400 μm PCS). The board includes a single RedLink® receiver premounted onto a simple PCB that allows easy application of DC power and monitoring of the output signal via a standard 0.1-inch header.

When paired with a transmitter evaluation board such as the EVAL-FT10MHNR, the EVAL-FR10DHIR can be used to quickly prototype and evaluate an optical link.

The unpopulated footprint (J2) for a PCB mounted SMA connector has been added to allow a secure connection to lab equipment such as a Bit Error Rate Tester (BERT).



INITIAL SETUP

- 1. Connect 3.3/5 V to the Rx VCC header (J1 Pin 1)
- 2. Connect GND of a DC power supply to the ground pin of the PCB header (J1 Pin 2)
- 3. To monitor Vout, connect to an oscilloscope channel with a 1 $M\Omega$ high impedance probe (J1 Pin 3)




FIGURE 1
Evaluation Board Schematic